

# VXA-710

## AIR BAND TRANSCEIVER

# SPIRIT



### Multi Band / Multi Mode Operation

- Air Band (108 MHz - 137 MHz) including NAV (108 MHz - 118 MHz) AM 5 W P.E.P. (1.5 W Carrier)
- Wide-Band FM Broadcast Receive 88 MHz-108 MHz
- US BRS Band Reception with CTCSS/DCS Decoder
- NOAA Weather Channel Receive with NOAA Severe Weather Alert (U.S.A. Only)

### True Heavy Duty Construction

- Rugged Magnesium Die-Cast Construction
- IPX7 Submersible (3 ft. 30 minutes)

### Ultimate Air-Band Features

- Long-Life Lithium-Ion Battery included
- RX Battery Saver Mode
- 160 Memories with Pre-programmed BOOK Memories
- Multi-Color Strobe LED for Status Indication and Emergency Light in Dark
- VOR Navigation Display
- Back-lit Keypad and Display with Dimmer
- One-Touch Emergency Frequency Access (121.5 MHz)



Actual Size

**IPX7**  
Submersible  
30 minutes @ 3 feet (1 m)

**Air Band**  
(108 MHz - 137 MHz)  
including NAV (108 MHz - 118 MHz)  
AM 5 W P.E.P. (1.5 W Carrier)



**FM Broadcast**  
Wide-Band Receive  
88 MHz - 108 MHz



**US BRS Band**  
US BRS Band Reception  
with CTCSS/DCS Decoder



**NOAA**  
Weather Channel Receive  
with NOAA Severe  
Weather Alert (U.S.A. Only)



# Vertex Standard Presents the Ultimate Air-Band Transceiver

# SPiRiT

AIR BAND TRANSCEIVER  
VXA-710

*Air Band Operation, VOR Navigation, FM Broadcast, and US BRS Band Reception included*

The multiple capabilities of the VXA-710 Spirit yield unmatched operating and monitoring opportunities for the owner on the go! Besides full voice transmit and receive operation on the Air Band, the VXA-710 Spirit also provides extensive VOR and CDI Navigation tools, along with convenient reception of the FM Broadcast band during down time. And you get the additional monitoring excitement afforded by receiver coverage of the Business Radio Service (BRS) band, a YAESU exclusive!

### 160 Memory Channels (Incl. Pre-programmed "Book" Memories)

The extensive Memory system of the VXA-710 includes 70 "Main" memories, plus ninety pre-programmed "Book" memories, for quick and easy recall of often-used frequencies. The memories may be labeled with a title, for quick recognition.

### Submersible (IPX7)

The VXA-710's case, speaker enclosure, and controls are carefully sealed against water ingress, allowing the transceiver to be specified for protection against water ingress per IPX7 specifications (immersion to 3 feet/1 m for 30 minutes). So you need not fear using your VXA-710 during severe weather.

### Rugged Magnesium Die-Cast Construction

The unmatched ruggedness of the VXA-710 is coupled with ultra-light weight, thanks to the die-cast magnesium case and chassis construction. Rubber bumpers on the bottom corners of the case protect it against damage from every-day bumps and scrapes.



Rugged Magnesium case with rubber bumpers and gaskets.

### Supplied Rechargeable Lithium-Ion Battery

The VXA-710 is supplied with a super-long-life 7.4 V, 1400 mAh Lithium-Ion Battery Pack (FNB-80LI), providing many hours of operation and reliable charging without the "memory" effects that can plague other battery types. With the optional CD-15A Charging Stand and NC-72B/C AC Adapter, the FNB-80LI may be charged in as little as 2.5 hours, so you'll quickly be ready for more operating action! And the optional FBA-23 Alkaline Battery Case will accept two "AA" batteries (not supplied) for low-power emergency operation. The VXA-710's EXT DC jack will also accept 12 Volts from the NC-72B/C directly (RX only), or from an external power supply.

### Receive Battery Saver

This feature helps maximize battery life by de-energizing the receiver section during periods of no activity, waking the receiver up at user-selected intervals to sample for channel activity. If no activity

### VOR NAVIGATION: AIR BAND

#### GENERAL VOR EQUIPMENT

COURSE Indicator  
COURSE Deviation Needle  
TWO-Degree Deviation Marks  
TO-"FROM" Flag Indicator

#### COM BAND (118.0000 - 136.9750 MHz)

VFO 128.8000

#### NAV BAND (108.0000 - 117.9750 MHz)

##### VOR MODE

VFO 113.6000

##### CDI MODE

5.0°

COURSE Indicator  
COURSE Deviation Needle  
TO-"FROM" Flag Indicator  
OVERFLOW Indicator  
TO-"FROM" Flag Indicator

is detected, the Spirit goes back into its "sleep" mode. Current consumption is significantly reduced, thereby maximizing battery life. This feature is only found on Vertex Standard Airband Transceivers.

### Multi-Color Strobe LED Status Indicator

Among the more innovative features introduced in the VXA-710 is the full-color Strobe LED, which provides indication of a number of transceiver status items using different colors. Different colors may be selected for each of the above conditions, and a total of 256 color shades are available, for customizing the colors just the way you like them.



### Dot Matrix Display

No Airband hand-held transceiver has a display that even compares to the VXA-710's 132 x 64 dot matrix display. Providing clear, easy-to-read indication of frequency and Navigation data alike, the VXA-710's display includes an unparalleled array of graphical and pictorial tools that make operation a breeze.

### NOAA WEATHER CHANNELS (U.S.A. Only)

The Spirit can receive all 10 NOAA weather broadcast frequencies. The Automatic Active Weather Channel Locator (a Vertex Standard exclusive) automatically scans for active NOAA weather stations in your area when WX band is selected.

### NOAA "Severe Weather" Alert (U.S.A. Only)

The Spirit can receive a special feature that sounds an alarm when the special "Severe Weather" alert tone is received from a Weather Broadcast station. This warns you of potentially life-threatening flying conditions.

### Backlit Keypad and Display with Dimmer

The front panel's keypad and LCD are illuminated in Vertex Standard's renowned Omni-Glow™ amber hue, for excellent visibility and minimal impact on your night vision. The Omni-Glow™ display/key illumination may be configured in a number of battery-saving ways. Both Brightness and Contrast are adjustable. You can set the illumination to appear



continuously, or only for a few seconds after a key is pressed. You can even turn the "Busy" Strobe off, for additional battery conservation.

### One Touch Emergency Frequency Access

For lightning-fast access to the 121.5 MHz Emergency Frequency, a dedicated key on the front panel assures you of no delays in summoning help in an emergency.

### PC PROGRAMMABLE

The channel configurations can be easily re-programmed in minutes using the optional PC Programming cable (CT-29+CT-97), software (CE75) and your PC. As your operating needs change, you can quickly re-program your Spirit with the important frequency data you need.

### CTCSS and DCS Decode in BRS Band Reception

SPECIFICATIONS	
<b>General</b>	
Frequency Range:	TX 118.000 - 136.975 MHz (COM Band), RX 88.000 - 108.000MHz (FM BC Band), 108.000 - 117.975 MHz (NAV Band), 118.000 - 136.975 MHz (COM Band), 151.5125 - 158.400MHz (BRS Channels), Weather Channel (WX-01 - WX-10)
Channel Spacing:	5/10/12.5/15/20/25/50/100 kHz
Emission Type:	TX: AM RX: AM & FM
Supply Voltage:	4.5 - 15.0 VDC
Current Consumption (approx.):	250 µA (Power off), 35 mA (Battery saver on, save ratio 1:5), 60 mA (Squelch on), 180 mA (Receive), 800 mA (Transmit AM: 1.5W Carrier @ 7.4V) 400 mA (Transmit AM: 0.3W Carrier @ 4.5V) -22° F to +140° F (-30° C to +60° C)
Temperature Range:	-22° F to +140° F (-30° C to +60° C)
Case Size (W x H x D):	2.36" x 3.78" x 1.12" (60 x 96 x 28.5 mm) w/FNB-80LI
Weight (approx.):	9.9 oz. (280 grams) with FNB-80LI, antenna
<b>Receiver</b>	
Circuit Type:	Double-conversion Superheterodyne
IFs:	35.4 MHz & 450 kHz (AM / NFM), 45.65 MHz & 10.7MHz (WFM)
Sensitivity:	88-108 MHz: < 2 µV (for 12 dB S/NAD with 1 kHz tone @ 22.5 kHz deviation) 108 MHz-136.975 MHz: < 1 µV (for 6 dB S/N with 1 kHz tone @ 30% modulation) BRS-01-BRS-21: < 0.32 µV (for 12 dB S/N with 1 kHz tone @ 3.5 kHz deviation) WX-01 - WX-10: < 0.4 µV (for 12 dB S/N with 1 kHz tone @ 3.5 kHz deviation)
Selectivity:	AM/FM: < 8 kHz/—6 dB, WFM: < 200 kHz/—6 dB
Adjacent Ch. Selectivity:	AM/FM: > 25 kHz/—60 dB, WFM: > 300 kHz/—20 dB
AF Output:	0.4W @ 8 Ohms, 10% THD @13.8 V
<b>Transmitter</b>	
Power Output:	118 MHz-136.975 MHz: AM: 5.0 W (PEP), 1.5 W (Carrier Power) @ 7.4 V
Frequency Stability:	Better than -2.5 ppm [-22° F to +140° F (-30° C to +60° C)]
Modulation System:	AM: Low Level Modulation, > 60 dB below carrier
Spurious Emission:	> 60 dB below carrier
Int. Microphone Type:	Condenser
Ext. Mic. Impedance:	150 Ohms

Specifications are subject to change without notice.

### Supplied Accessories:

Li-ion Battery Pack(7.2 V, 1400mAh) FNB-80LI,  
Battery Charger NC-72, Helical Antenna ATV-9,  
Headset Cable CT-96, Operating Manual, Warranty Card

### ACCESSORIES & AVAILABLE OPTIONS

MH-44B46 Speaker Microphone	FBA-23 2 x "AA" Cell Battery Case (batteries not supplied)	CD-15A Desktop Rapid Charger	E-DC-5B DC Cable w/Noise Filter	E-DC-6 DC Cable; plug and wire only	CN-3 Antenna Adapter

About this brochure: We have made this brochure as comprehensive and factual as possible. We reserve the right, however, to make changes at any time in equipment, optional accessories, specifications, model numbers, and availability. Precise frequency range may be different in some countries. Some accessories shown herein may not be available in some countries. Some information may have been updated since the time of printing; please check with your Authorized Vertex Standard Dealer for complete details.



VERTEX STANDARD CO., LTD.

4-8-8 Nakameguro, Meguro-ku, Tokyo 153-8644, Japan

For our latest product news, visit us on the Internet:  
<http://www.vxstd.com>

VERTEX STANDARD <http://www.vertexstandard.com>

US Headquarters E-mail: [yaesuavionics@vxstdusa.com](mailto:yaesuavionics@vxstdusa.com)  
10900 Walker Street, Cypress, CA 90630, U.S.A. Phone 714/827-7600; Fax 714/827-8100

YAESU EUROPE B.V.

P.O. Box 75525, 1118 ZN Schiphol, The Netherlands

YAESU UK LTD. <http://www.yaesu.co.uk>

E-mail: [sales@yaesu.co.uk](mailto:sales@yaesu.co.uk)  
Unit 12, Sun Valley Business Park, Winnall Close  
Winchester, Hampshire, SO23 0LB, U.K.

VERTEX STANDARD HK LTD. <http://www.vxstd.com.hk>

Unit 5, 20/F., Seaview Centre, 139-141 Hoi Bun Road,  
Kwun Tong, Kowloon, Hong Kong